

Sparkle Power Inc. A Leading Power Supply Manufacturer Web site: <u>www.sparklepower.com</u>

FSP250-50FEB (Meet 80plus Bronze, RoHS Compliant) 250 Watts Flex ATX Switching Power Supply

Features

- Complied with Flex ATX and ATX12V standard
- Active Power Factor Correction (PFC) meet EN61000-3-2
- High efficiency and reliability
- Compatible with European Union Directive 2011/65/EU & (EU)2015/863 (Restriction on Hazardous Substances).
- Remote ON/OFF function
- Internal 12V DC fan included
- Low noise and ripple
- Output over voltage, short circuit, and over current protection
- 100% Hi-pot, ATE, and burn-in tested
- Re-settable power shut down
- Complies with FCC part 15 subpart J class B 115Vac operation, and CISPR 32 class B at 230Vac operation
- Approved by CB 62368 & 60950-1 2nd, EMC. CUL/UL TUV, FCC, CE

Input Characteristics

Input Range: 90 ~ 264Vac (RMS), Full Range Input Frequency: 47 ~ 63Hz Input Current: Max 4A (RMS) @ 115Vac, 2A (RMS) @ 230Vac Inrush Current: No damage.

Output Characteristics





Specification

- Temperature Range: Operating: 0°C ~ +50°C; storage : -20°C ~ +80°C
- Humidity: 85% RH, Non-condensing on operating, 95%RH, Non-condensing on storage.
- **Dielectric Withstand:** Primary frame ground 1800V AC for 2 second
- Efficiency: Typical > 85%
- Altitude: The power supply is applied for tropical climates and use at altitudes not exceeding 5000m above Sea level
- Standby Power Consumption (5Vsb):
 Efficiency> 45% @5Vsb/45mA &230Vac input (2013 Lot 6)
 Efficiency> 55% @ 5Vsb/550mA &230Vac input
 Efficiency> 70% @ 5Vsb/1A &230Vac input
 Efficiency > 70% @ 5Vsb/2.5A &230Vac input
- Rise time: Less than 20ms
- Hold-up Time: 16ms minimum at 80% load.
- **Power Good Signal:** Power on delay time 100 ~ 500ms, off delay 1ms minimum (TTL and CMOS compatible)
- Leakage Current: Less than 3.5mA at 264Vac, 50Hz
- **MTBF:** A minimum predicted MTBF (MIL-HDBK-217) of 100,000 hours of continuous operation at +25°C.
- Dimensions (LxWxH):150x81.5x40.5mm /6x3.2x1.6inch

Output Voltage	Minimum Load	Maximum Load	Load Reg.	Ripple & Noise
+3.3V	0A	12.0A	± 5%	50mV P-P
+5V	0A	14.0A	± 5%	50mV P-P
+12V	0A	18.0A	± 5%	120mV P-P
-12V	0A	0.3A	± 10%	120mV P-P
+5Vsb	0A	2.5A	± 5%	50mV P-P

*+3.3V and +5V total output not exceed 80W

* Total output for this subject power supply is 250W

Sparkle Power Inc. Main Office 48502 Kato Road. Fremont CA 94538 TEL: 408-519-8888 FAX: 408-519-9999 E-MAIL: info@sparklepower.com Sparkle Power Inc. Los Angeles Office 17071 Green Drive City of Industry, CA 91745 TEL: 626-839-7180 FAX: 626-839-3395